

GUJARAT TECHNOLOGICAL UNIVERSITY
BE- SEMESTER-IV (NEW) EXAMINATION – WINTER 2020

Subject Code: 3141009

Date: 19/02/2021

Subject Name: Electromagnetic Theory

Time: 02:30 PM TO 04:30 PM

Total Marks: 56

Instructions:

1. Attempt any FOUR questions out of EIGHT questions.
2. Make suitable assumptions wherever necessary.
3. Figures to the right indicate full marks.

		MARKS
Q.1	(a) Differentiate between position and distance vector with appropriate example	03
	(b) Given vectors $A = 3a_x + 4a_y + a_z$ and $B = 2a_y - 5a_z$, find angle between vector A and B	04
	(c) Derive an equation of electric field due to surface charge distribution.	07
Q.2	(a) Derive a relation between electric flux and electric flux density.	03
	(b) How electric dipole is formed? Derive an equation of electric field due to electric dipole.	04
	(c) A parallel-plate capacitor with plate area of 5 cm^2 and plate separation of 3 mm has a voltage $50\sin 10^3 t$ V applied to its plates. Calculate the displacement current, assuming $\epsilon = 2\epsilon_0$.	07
Q.3	(a) Derive an equation for variation in flux by stationary loop in time varying magnetic field.	03
	(b) State and explain the Faraday's law in detail	04
	(c) What is the application of Poynting's Theorem? Derive its equation for total power leaving the volume.	07
Q.4	(a) Derive an equation for variation in flux by moving loop in static magnetic field.	03
	(b) Briefly describe point and integral form of Maxwell's equation.	04
	(c) Explain the significance of skin depth. Also derive an equation of intrinsic impedance of good conductor.	07
Q.5	(a) The electric field in free space is given by $E = 50 \cos (10^8 t + \beta x) a_y$ V/m Calculate β and the time it takes to travel a distance of $\lambda/2$	03
	(b) Describe characteristics of different medias for EM wave propagation.	04
	(c) Derive an equation of Reflection Coefficient in terms of intrinsic impedance of two different media.	07
Q.6	(a) In free space, $H = 0.1 \cos (2 \times 10^8 t - kx) a_y$ A/m. Calculate K , λ and time period T .	03
	(b) Explain vector wave equation with its importance in plane wave propagation.	04
	(c) Derive and sketch the standing wave pattern when the intrinsic impedance of medium 1 is less than medium 2 ($\eta_1 < \eta_2$).	07

- Q.7** (a) Define following **03**
1. Propagation Vector
2. Angle of Incident
- (b) Explain and sketch any four types of Transmission Line **04**
- (c) An air line (lossless) has characteristic impedance of 70Ω and phase constant of 3 rad/m at 100 MHz . Calculate the inductance per meter and the capacitance per meter of the line. **07**
-
- Q.8** (a) Define following **03**
1. Plane of Incidence
2. Polarizing Angle
- (b) Derive characteristic equation of lossless transmission line **04**
- (c) An EM wave travels in free space with the electric field component $E_s = 100 e^{j(0.866y+0.5z)} a_x \text{ V/m}$, Determine ω and λ **07**

GTUQuestionPapers.com